

PLASMA CUTTING

Serie ZETA® NO HF



CE EN60974-7



CODE	↔	☐
------	---	---

PAZ006D-000-FA3	6 m	19.7'	
PAZ008D-000-FA3	7,6 m	25'	
PAZ015D-000-FA3	15,2 m	50'	

PAZ006D-004-FA3	6 m	19.7'	
PAZ008D-004-FA3	7,6 m	25'	
PAZ015D-004-FA3	15,2 m	50'	

PAZ006D-100-FA3	6 m	19.7'	
PAZ008D-100-FA3	7,6 m	25'	
PAZ015D-100-FA3	15,2 m	50'	

PAZ006D-200-FA3	6 m	19.7'	
PAZ008D-200-FA3	7,6 m	50'	
PAZ015D-200-FA3	15,2 m	50'	

PAZ006D-304-FA3	6 m	19.7'	
PAZ008D-304-FA3	7,6 m	25'	
PAZ015D-304-FA3	15,2 m	50'	

TECHNICAL DATA					
----------------	--	--	--	--	--

	NO HF	40 A	60 A	80 A	110 A	130 A
		0,4 kg	0,4 kg	0,4 kg	0,4 kg	0,4 kg
		0,88 lb	0,88 lb	0,88 lb	0,88 lb	0,88 lb
	PEAK	500	500	500	500	500
		5 bar	5 bar	5 bar	5 bar	5 bar
		110 l/m	120 l/min	140 l/min	155 l/m	180 l/m
	X 60%	40A	60A	80A	110A	130A
	X 100%	30A	45A	65A	85A	105A
		15 mm	25 mm	32 mm	40 mm	45 mm
		3/5"	1"	1 1/4"	1 3/5"	1 3/4"



	CODE		Ø	↔	STARTER KIT					PCS X	X	
					PT1040	PT1060	PT1080	PT1110	PT1130			
					40 A	60 A	80 A	110 A	130 A			
1	CV0363P					•	•	•			1	2
1	CV0364P							•			1	2
1	CV0365P								•		1	2
2	PC0360P				•	•	•	•	•		1	2
3	PD0360P08				•						5	2
3	PD0360P10					•					5	2
3	PD0360P13						•				5	2
3	PD0361P15						•				5	2
3	PD0362P17							•			5	2
4	PE0360P				•	•	•	•	•		1	2
5	PR0360P				•	•	•				5	2
5	PR0361P							•	•		5	2
6	FH1602P				•	•	•	•	•		1	2

	CODE			
7	EA1920			
7	PF0360			
8	BX0910			
8	PT0361			
8	PT0362			
9	TP0360			1
10	PH0908-06		6m - 1/4 G	1
10	PH0908-08		7,6m - 1/4 G	1
10	PH0908-15		15m - 1/4 G	1
11	BW0147		cable support	1
11	FY0043		Central Adaptor	1
12	FY0090		TRAFIMECTOR®	1

	CODE	GOUGING	40 A	60 A	80 A	110 A	130 A	PCS X	X
1	CV0370P		•	•	•			1	2
1	CV0371P					•		1	2
1	CV0372P						•	1	2
3	PD0370P16		•	•				5	2
3	PD0370P18				•			5	2
3	PD0370P20					•		5	2
3	PD0370P22						•	5	2